KOWA.001A PATENT

ROTATING DISPLAY SYSTEM

Cross-Reference to Related Applications

This application claims the benefit of provisional patent application 60/242,961 entitled *Electronic Rotating Display*, filed October 24, 2000.

Reference to Computer Program Listing Appendix

This application incorporates by reference a computer program listing appendix, referred to herein as *Appendix C* and contained on each of two identical CD-R discs submitted herewith as filename: KOWA.001A Appendix.C; size: 24 KB; created: 10/22/2001.

Background of the Invention

Electronic displays are pervasive in the modern world. Various incarnations of cathode-ray tube, vacuum florescent, light emitting diode (LED), liquid crystal display (LCD) and more recently laser diode and light valve technologies are applied in electronic devices used to visually transfer information. Common displays typically provide visual information arranged as pixels or vectors in a two-dimensional plane. The information transmitted by the device is usually alphanumeric or graphical in nature. The content of the information is only limited by the imagination of the purveyors.

Summary of the Invention

Advances in microcontroller technology and electronics in general have created the possibility of new and interesting methods of displaying text and graphics. For example, LED displays placed in motion and modulated in a controlled manner can cause stable characters to appear as the result of a phenomenon known as "persistence of vision." Practical and inexpensive persistence-of-vision display products, however, are not currently available. Some devices rely on manually-generated motion, creating a non-uniform display and requiring battery power. On these devices, messages must be input manually and cannot be controlled or programmed via an external interface. Other devices rely on a pendulum motion to create the display surface. The pendulum constrains the horizontal width of the display by the vertical height of the display member. In other words, in order to maintain a reasonably substantial, linear, horizontal display area, the height of the device must be proportionally greater. This forces the overall size of the

product to be at least 3 or 4 times higher than it is wide. The current designs also lack any kind of remote operation or programming capability.

One aspect of the present invention is a display system comprising a base and an electric motor supported by the base. A shaft extends from the motor and is operable so as to rotate when power is applied to the motor. An elongated, generally planar display assembly is center mounted to the shaft so that the display assembly rotates as the shaft rotates. A light array is mounted to an end portion of the display assembly so as to sweep out a generally cylindrical path as the display assembly rotates. An elongated, generally planar control assembly is fixedly mounted to the base between the motor and the display assembly. The control assembly is configured to accommodate the shaft, and an inductive coupling is adapted to provide electrical communications between the control assembly and the display assembly.

In one embodiment, the display system further comprises a first switch located on the control assembly configured to transfer power from a power source to the inductive coupling and a power block located on the display assembly configured to transfer power from the inductive coupling to the display assembly. The display system may further comprise a first processor located on the control assembly and operable to generate a plurality of display commands and a second switch located on the control assembly and in electrical communications with the first processor, where the second switch is configured to transfer the display commands to the inductive coupling. Also, a second processor may be located on the display assembly, and a data block may be located on the display assembly configured to transfer the display commands from the inductive coupling to the second processor. The second processor may be operable to transfer display data to the light array according to the display commands.

In a particular embodiment, the display system may further comprise a sensor output responsive to a position of the display assembly relative to the control assembly, the first processor in communications with the sensor output so as to generate a trigger command to the second processor, the trigger command incorporating a variable trigger delay, the trigger command indicating the apparent position of a pixel display. The display system may also further comprise a push button switch operable in conjunction

with a menu presented on the pixel display so as to set an operational mode. In addition, the display system may further comprise a plurality of display language instructions for display specific tasks, the display language instructions interpreted by the first processor so as to generate the display commands. The inductive coupling may comprise a first inductive coupler mounted on the display assembly concentric with the shaft and a second inductive coupler mounted on the control assembly concentric with the shaft, the first inductive coupler and the second inductive coupler maintained at a fixed distance apart. The sensor may comprise a Hall-effect sensor mounted on the control assembly and a magnet mounted on a base portion of the shaft so that the magnet repeatedly passes under the Hall-effect sensor as the shaft rotates.

Another aspect of the rotating display system according to the present invention provides an inexpensive way of synthesizing a warped two-dimensional, e.g. cylindrical, plane of display elements used for visually transmitting information. In one embodiment, the display sweeps text, such as time, date, day of the week, custom messages, graphics and animations in a cylindrical plane using a vertical light array comprised of a column of modulated light emitters. A display assembly may be spun by any electromechanical or electromagnetic means. For example, the display assembly may be mounted to a shaft of a brushless DC motor. As the rotation of the light array increases, the visibility of the light array decreases. Thus when the rotating display system is operating, it appears as though the information displayed is suspended in air, following a contour of an invisible cylindrical plane. This effect draws attention to the display and, thus, to the messages or images it transmits. In one embodiment, power and data are both provided to the rotating display assembly inductively. Hence, there is no physical electrical connection between the stationary and moving assemblies. Thus, there are no slip rings or brushes that would reduce the life of the display system.

In one embodiment, the display system may be updated in real time. This implies that the display is not limited to "canned" or pre-programmed static messages. Data can be transferred to the rotating display assembly to generate 2-D scrolling and animation effects as well as to update the text of the display electronically via a separate data source. For example, with an appropriate interface the display system could be used in

conjunction with an electronic network to display stock quotes. The display data may scroll 360 degrees on a cylindrical plane. A person may view the display from any vantage surrounding the display. The display data is bit-mapped. Thus any alphanumeric characters as well as custom icons or graphics can be output for static or animated effects.

In another embodiment, the display system has a simple one-button interface. The mode or action of the display can be changed using the button for selection coupled with an appropriate menu algorithm. For example, if the display system is being used as a clock and the user would like to set the clock, the user would initiate a menu mode by pressing the button. Then, when an appropriate menu item such as "Set Clock?" appears, the user would again press the button. This would initiate a mode where the display would cycle through the hours on the clock. When an appropriate hour such as 3:00 PM is displayed, the user again presses the button, thus selecting the hour of the day.

In a further embodiment, various aspects of the display system are microprocessor controlled. This allows flexibility with regards to the operation of the display system, especially considering that the display system includes re-programmable nonvolatile memory. This memory includes program and data space that allow the operation of the display system to be customized and numerous messages and images to be stored and displayed according to the particular program operating the apparatus. The display system may be programmed externally via a computer cable and adapter. This feature allows re-sellers to program the unit with their own appropriate functions and messages to target a particular market segment. Further, end users may program the unit to suit their own particular needs. The display system is also remotely controllable so that messages and images are dynamically changed and displayed. In one embodiment, the display system includes an internal clock and calendar. This gives the display system a self-contained ability to display messages based on holidays, anniversaries or user defined events. It also allows the display system to change mode based on time.

A further aspect of the present invention is a display method comprising the steps of describing a pixel display with a display instruction, interpreting the display instruction so as to create a display command, and generating a data signal responsive to the display command. Further steps comprise deriving a plurality of column data responsive to the

data signal, rotating a display assembly about an axis so that a light array mounted on the display assembly sweeps along an arc surface, and modulating the light array with the column data so as to create a viewable area of the pixel display across at least a portion of the arc surface.

In one embodiment, the display method comprises the further steps of combining a power source and the data signal into a waveform, inductively coupling the waveform to the display assembly, filtering display assembly power from the waveform, and decoding the data signal from the waveform. The waveform may be a square wave, where the data signal is a plurality of bits and the combining step comprises the substeps of switching the power source so as to generate the square wave, interrupting the square wave for a first time period in response to each of the bits that is a one, and interrupting the square wave for a second time period in response to each of the bits that is a zero. In a particular embodiment, the square wave has a time period of T and the first time period is about 10T, the second time period is about 20T, and the decoding step comprises the substeps of generating a zero bit if the square wave ceases for a time period greater than 15T and generating a one bit if the square wave ceases for a time period less than 15T.

In another embodiment, the display method comprises the further steps of sensing a trigger position of the display assembly, adding a variable delay to the trigger position so as to create a virtual trigger position, initiating the modulating step in response to the virtual trigger position, and adjusting the variable delay so as to position the viewable area. In a particular embodiment, the display method comprises the further steps of designating a front position for the pixel display, calculating the viewable area from a rotational speed of the display assembly and a number of columns of the pixel display, and determining the variable delay from the viewable area and the trigger position so as to position a center of the viewable area at the front position. Further aspects of the rotating display system will become apparent from a consideration of the drawings and ensuing description.

Brief Description of the Drawings

FIGS. **1A-B** are perspective and exploded views, respectively, of a rotating display system;

FIGS. **2A-B** are top and bottom perspective views, respectively, of a control assembly;

FIGS. **3A-C** are top perspective, bottom perspective, and exploded views, respectively, of a display assembly;

FIG. **4** is a perspective view of a shaft mate;

FIG. **5** is a perspective view of a shaft;

FIG. **6** is a functional block diagram of a control assembly;

FIG. **7** is a functional block diagram of a display assembly;

FIG. **8** is a detailed functional block diagram of inductive power transfer and data communications aspects of the control and display assemblies;

FIG. **9** is a top-level software flow diagram of a rotating display system;

FIG. **10** is a detailed flow diagram of a system software embodiment;

FIG. **11** is a detailed flow diagram of control assembly software; and

FIG. **12** is a detailed flow diagram of display assembly software.

Detailed Description of the Preferred Embodiments

FIGS. **1-12** illustrate a rotating display system **100**. In particular, FIGS. **1-5** illustrate mechanical hardware aspects of a rotating display system **100**. Also, FIGS. **6-8** illustrate electrical hardware aspects of a rotating display system **100**. Further, FIGS. **9-12** illustrate software aspects of a rotating display system **100**.

Hardware Configuration

Mechanical

FIGS. **1A-B** illustrate a mechanical hardware configuration for a rotating display system **100**. As shown in FIG. **1A**, the display system **100** has a control assembly **200**, a display assembly **300**, a light array **330** mounted on the display assembly **300**, and a motor **160** mounted on and supported by a base **170**. The control assembly **200** has a processor **610** (FIG. **600**) that controls display rotation, processes display data and transmits data to the display assembly **300**, as described with respect to FIGS. **6**, **8** and

11, below. The display assembly **300** has a processor **710** (FIG. **7**) that receives display data and formats it for the light array **330**, as described with respect to FIGS. **7**, **8** and **12**, below.

As shown in FIG. **1B**, the display system **100** also has a shaft mate **400** and a shaft **500**. The shaft **500** is attached to the motor **160** and, in conjunction with the shaft mate **400**, supports the display assembly **300**, as described with respect to FIGS. **4-5**, below. The control assembly **200** and motor **160** are secured to the base **170** using mounting screws **72** inserted through spacers **74** and washers **76** and threaded into base mounting holes **172**. The spacers **74** separate the motor **160** and the control assembly **200** by a fixed distance, which is approximately 1/8 inch in one embodiment. The washers **76** are mounted between the motor **160** and the base **170**, and, alternatively, may be rubber grommets. In one embodiment, the motor **160** is a brushless DC motor, although the display assembly **300** may be spun by any electromechanical or electromagnetic apparatus.

When power is applied to the display system **100**, the control assembly processor **610** (FIG. **6**) switches on the motor **160** and the display assembly **300** spins up to operating speed, which is approximately 900 rpm in one embodiment. Once the display assembly **300** has spun up, the control assembly processor **610** (FIG. **6**) turns on the display assembly **300** and advantageously sends both power and data, such as commands, display data and trigger information, across an inductive coupling **220** (FIGS. **2A-B**), **320** (FIGS. **3A-C**) to the display assembly processor **710** (FIG. **7**). The display assembly processor **710** (FIG. **7**) interprets the information sent by the control assembly processor **610** (FIG. **6**) and modulates the light array **330** with column data. The column data is presented on a pixel display such that an observer sees words, characters, icons and/or any other pixel-based shapes contained in a control assembly memory **620** (FIG. **6**). In one embodiment, the effective size of the pixel display is 60 pixels wide by 8 pixels high and can move 360 degrees around the axis of the display assembly **300**.

The partitioning of the display system electronics between a fixed control assembly **200** and a rotating display assembly **300** advantageously allows user input via

a push button switch **240** (FIG. **2A**) while the pixel display is operating. Further, because the pixel display is operating, this feature allows user interaction with the pixel display via a menu selection process, as described below. That is, because display system control is implemented on a fixed control assembly **200**, it is unnecessary for the user to stop rotation of the display assembly **300** and perform a "blind" input process. Also, providing a fixed control assembly **200** advantageously allows the pixel display to be updated during operation utilizing a standard interface to the outside world, as described below. For example, stock quotes may be loaded into the pixel display in real time via an I2C bus.

FIGS. **2A-B** illustrate one embodiment of the control assembly **200**, which has a control assembly printed circuit board (PCB) **210**, an inductive coupler **220**, a push-button switch **240**, a power jack **260**, and a Hall-effect sensor **280**. The control assembly components are mounted on and interconnected by the PCB **210**, which is a substrate carrying conductive traces, as is well-known in the art. The PCB **210** has a generally planar and elongated shape with a first side **211**, an opposite second side **212**, a first end **214**, an opposite second end **216**, a center hole **218** and a pair of mounting holes **219** located on either side of the center hole **218**.

As shown in FIGS. **2A-B**, the inductive coupler **220** has a cylindrical cavity **222** and is mounted on the first side **211** at the center of the PCB **210** such that the cylindrical cavity **222** is aligned with the PCB center hole **218**. The control assembly inductive coupler **220** works in conjunction with the display assembly inductive coupler **320** (FIGS. **3A-B**) to transmit power, commands, data and trigger information between the control assembly **200** and the display assembly **300**, as described with respect to FIGS. **6-8**, below.

Also shown in FIGS. **2A-B**, the push-button switch **240** is mounted on the second side **212** proximate the first end **214**. The push-button switch **240** functions in conjunction with a menu presented on the rotating display system **100** to set the mode or action of the display **100**, as described with respect to FIGS. **10-11**, below. The power jack **260** is mounted on the second side **212** proximate the second end **216** and is

configured to mate with a corresponding external plug are to supply power to the display system **100**, as described in detail with respect to FIGS. **6-8**, below.

Further, FIG. **2B** shows that the Hall-effect sensor **280** is mounted on the second side **212** and positioned on the PCB **210** so that the shaft magnet **554** (FIG. **5**) will pass directly under it as the shaft **500** (FIG. **5**) spins. In one embodiment, both the shaft magnet **554** (FIG. **5**) and the sensor **280** are located approximately ¼ inch off the control assembly **200** center of rotation. The Hall-effect sensor **280** provides a trigger pulse that indicates the rotational position of the display assembly **300** (FIGS. **3A-C**) as it spins, allowing the synchronization of display information, as described with respect to FIG. **11**, below.

FIGS. **3A-C** illustrate one embodiment of the display assembly **300**, which has a display assembly PCB **310**, an inductive coupler **320**, a light array **330** and a counterweight **340**. The display assembly components are mounted on the PCB **310**, which has a generally planar and elongated shape with a first side **311**, an opposite second side **312**, a first end **314** and an opposite second end **316**. The PCB **310** has a center hole **318** placed at the rotational center of the display assembly **300**.

As shown in FIGS. **3A-C**, the inductive coupler **320** has a centered cylindrical cavity **322** and is mounted on the second side **312** of the display assembly PCB **310** such that the cavity **322** is aligned with the PCB center hole **318**. In one embodiment, the control assembly inductive coupler **220** (FIGS. **2A-B**) and the display assembly inductive coupler **320** are each constructed from a standard 14x8 pot core wound with 35 turns of 31-gauge magnet wire.

Also shown in FIGS. **3A-C**, the light array **330** is mounted proximate the first end **314**. The light array **330** is comprised of 8 elements **332** which are surface-mount LEDs with associated current-limiting resistors mounted on a light array PCB **333**. A 9-pin 75-degree connector **334** connects the display assembly PCB **310** and the light array PCB **333**. The counterweight **340** is mounted on the second side **312** proximate the second end **316** so as to balance the display assembly **300** at the center hole **318**.

Although the control assembly **200** (FIG. **2A**) and the display assembly **300** (FIG. **3A**) have been described as implemented with PCBs, one of ordinary skill in the

art will recognize that these assemblies may be implemented with other circuit technologies, such as flexcircuits or hybrid circuits, and other support materials of various shapes and sizes within the scope of the present invention. Further, the light array **330** (FIG. **3A**) may comprise any number of elements and/or columns, and the elements may utilize various light emitting or light transmitting technologies.

FIG. **4** illustrates a shaft mate **400**, which has a circular disk **402** with a mate surface **442**, a mate end **446** distal the mate surface **442**, and a mate notched joint **404** extending normally from the mate surface **442** between the circular disk **402** and the mate end **446**. The mate notched joint **404** has a generally cylindrical portion proximate the mate surface **442** and a generally semi-cylindrical portion having a flat mate face **444** proximate the mate end **446**. The shaft mate **400** is mounted to the display assembly **300** (FIGS. **3A-C**) with the disk **402** concentric with the PCB center hole **318** (FIG. **3A**), the mate surface **442** bonded to the PCB first side **311** (FIG. **3A**), and the mate notched joint **404** extending through the PCB center hole **318** (FIG. **3A**) and into the inductive coupler cylindrical cavity **322** (FIG. **3B**).

FIG. **5** illustrates the shaft **500**, which has a circular base **502**, a cylindrical spindle **504**, a shaft notched joint **506** and a shaft end **516**. The shaft notched joint **506** has a generally cylindrical portion attached to the spindle **504** and a generally semi-cylindrical portion having a flat shaft face **552** proximate the shaft end **516**. A magnet **554** is mounted to the base **502**. The shaft **500** and shaft mate **400** (FIG. **4**) are attached with the shaft face **552** bonded to the mate face **444** (FIG. **4**). The diameter of the shaft notched joint **506** is such that it passes freely through the controller assembly inductive coupler **220** (FIGS **2A-B**). The shaft height is such that the controller assembly inductive coupler **220** (FIGS **2A-B**) and the display assembly inductive coupler **320** (FIGS. **3A-C**) are maintained at a fixed distance apart, which is less than 5mm in one embodiment. The magnet **554** is located on the base **502** such that when the display **330** (FIGS. **3A-C**) is 60 degrees from the front, it passes under the Hall-effect sensor **280** (FIG. **2B**), where the front is the location of the push button **240** (FIG. **2A**).

There is an important relationship among the trigger position, the rotational speed of the display assembly and the size of the apparent viewable display area. A

trigger is sensed when the magnet **554** passes under the Hall-effect sensor **280** (FIG. **2B**). The position of the light array **330** (FIG. **3A**) at this point is about 60 degrees to the left of center as one views the front of the display where the button **240** (FIG. **2A**) is located. The display assembly **300** (FIGS. **3A-C**) sweeps in a counter-clockwise direction when viewed from above. So after passing the trigger position, the light array elements **332** (FIG. **3A**) sweep from left to right when the display is viewed from the front.

A delay variable is utilized in the transmit trigger data block **1170** (FIG. **11**) so that a virtual trigger position is realized. This is useful for adjusting the center of the apparent display data viewed from the front of the display. As the light array elements **332** (FIG. **3A**) sweep an arc past the trigger position, the elements **332** (FIG. **3A**) are modulated. Assuming all pixels on the display are on, all elements **332** (FIG. **3A**) are turned on for 80 μs, then off for 200 μs and so on until 60 cycles are completed. Because there is a column of 8 light array elements **332** (FIG. **3A**), this creates an apparent 8 high by 60 wide pixel display. When the elements **332** (FIG. **3A**) are modulated starting at the same trigger position on each rotation, the pixels appear fixed in space around the cylindrical sweep of the display assembly **300** (FIGS. **3A-C**). This phenomenon is known as "persistence of vision".

At a rotational speed of 800 rpm (about 13 rotations a second), the total time for 1 revolution is 75ms. For a 60-column display where each column takes 280 μs to display, this equates to 16.8 ms for the total display time. So at 800 rpm, the viewable display area is about 80 degrees. In order to center the viewable area on the front of the display, the trigger position should be 40 degrees to the left of center. Since the magnet **554** (FIG. **5**) is aligned to the display assembly **300** (FIGS. **3A-C**) such that the trigger position is 60 degrees to the left of center, a delay of 20 degrees must be added between the actual trigger position and the "virtual" trigger position. Note that if the motor **160** (FIGS. **1A-B**) were controlled at a greater speed, the apparent size of the display would widen. For example, if the motor **160** (FIGS. **1A-B**) were spinning at 1000 rpm, the viewable display area would grow to about 100 degrees, as compared with 80 degrees at 800 rpm.

Electrical

FIGS. **6-7** illustrate an electrical hardware configuration for a rotating display system **100** (FIG. **1A**). FIG. **6** illustrates control electronics **600** residing on the control assembly **200** (FIGS. **2A-B**). FIG. **7** illustrates display electronics **700** residing on the display assembly **300** (FIGS. **3A-B**). As shown in FIG. **6**, the control electronics **600** has a control processor **610**, a control memory **620**, a real time clock **630**, a power regulator **640**, an oscillator **650**, an external interface **660**, a motor power switch **670** and coupling switches **680**. The control electronics **600** also interconnect with the Hall-effect sensor **280** and the inductive coupler **220**, described with respect to FIGS. **2A-B**, above.

As shown in FIG. **6**, the control electronics **600** have a DC voltage input **642** received through a power jack **260** (FIG. **2B**). The DC voltage **642** is applied to a power regulator **640**, which in one embodiment is a standard +5V voltage regulator having input and output filter capacitors. The power regulator **640** provides power to the processor **610** and other logic-level circuitry. The DC voltage **642** is also applied to the oscillator **650**, the motor power switch **670**, and the coupling switches **680** through the inductive coupler **220**. The motor power switch **670** and the coupling switches **680** utilize field effect transistors (FETs) to switch the DC voltage **642**. A processor output **612** controls the motor power switch **670** so as to couple the DC voltage **642** to the motor **160** (FIGS. **1A-B**). An oscillator output **652** controls a first switch **810** (FIG. **8**) of the inductive coupling switches **680**. Another processor output **614** controls a second switch **820** (FIG. **8**) of the inductive coupling switches **680**. The inductive coupling switches **680** transfer DC power to the inductive coupler **220** (FIGS. **2A-B**), as described with respect to FIG. **8**, below.

Also shown in FIG. **6**, an external interface output **664** is input to the processor **610** and to memory **620** so as to allow an external device to communicate with the processor **610** and to program memory **620**. The Hall-effect sensor **280** has an output **616** to the processor **610** so as to provide a virtual trigger position, as described with respect to FIG. **5**, above. The memory **620** has a non-volatile portion containing control

software that functions as described with respect to FIG. **11**, below. The real-time clock **630** is used to provide the time, day of week and date for display.

As shown in FIG. **7**, the display electronics **700** has a display processor **710**, a display memory **720**, a power block **730** and a data block **740**. The power block **730** and data block **740** receive power and data from the control electronics **600** (FIG. **6**) via the inductive coupler **320**, as described with respect to FIG. **8**, below. The power block output **734** supplies power to the processor **710**, memory **720** and other logic-level circuitry. The data block output **744** provides a data input to the processor **710**. A processor output **712** drives the light array **330**. The memory **720** has a non-volatile portion containing display software that functions as described with respect to FIG. **12**, below.

Power Distribution

FIG. **8** illustrates the one way power and data transfer mechanism between portions of the control electronics **600** and portions of the display electronics **700**. The switches **680** include a first switch **810** and a second switch **820** connected in series between the inductive coupler **220** and ground. The first switch **810** is actuated by the oscillator output **652**. The second switch **820** is actuated by the processor output **614**. Applying power to the display electronics **600** is realized by closing the second switch **820**. This allows the oscillator output **652** to modulate the first switch **810**, producing a square wave through the inductive coupler **220** based on the voltage of the DC power source **642**. The control assembly inductive coupler **220** couples the square wave to the display assembly inductive coupler **320**. The effect is to produce a similar square wave across the display assembly inductive coupler **320**, with losses due to the gap between the two couplings **220**, **320**.

As shown in FIG. **8**, the display assembly inductive coupler **320** feeds a square wave output **732** into the power block **730** and data block **740**. The power block **730** has a half-wave rectifier **830**, a low pass filter **840** and a voltage regulator **850**. The half-wave rectifier **830** removes portions of the square-wave output **732** to generate a rectified output **832**. The filter **840** smoothes the rectified output **832** to generate a filtered output **842**. The regulator **850** regulates the filtered output **842** to provide the

display power **734** for the display electronics **700** (FIG. **7**), as described with respect to FIG. **7**, above. In one embodiment, the oscillator output **652** has a 1 MHz frequency, i.e. a 1 μsec period T, and the power output **734** is +5V DC.

Communications

As shown in FIG. **8**, the display assembly inductive coupler **320** also feeds the square wave output **732** into the data block **740** through a diode (not shown). The data block **740** has a low pass filter **860** and a data sampler **870**. When a continuous square wave is applied to the low pass filter **860**, the filter output **744** is a continuous logic "high." A data bit is transferred through the coupling **220, 320** when the control processor output **614** interrupts the square wave momentarily by opening the second switch **820**. As the square wave ceases, the filter output **744** decays to a logic "low."

The data sampler **870** is realized by the display processor **710** (FIG. **7**) and associated display assembly software **1200** (FIG. **12**), which samples the filter output **744**. As the output **744** transitions from a logic "high" to a logic "low," the display assembly software **1200** (FIG. **12**) measures the time the signal stays "low." If the time is greater than 15 oscillator cycles, i.e. 15T, the transmitted data bit is determined to be "0." If the time is less than 15 oscillator cycles, 15T, the transmitted data bit is determined to be "1." Accordingly, the second switch **820** is opened for a time of 20T for a "0" and opened for a time of 10T for a "1." Eight bits are detected in this way per transmission from the control assembly **600**.

In this manner, a data path is created from the control assembly **600** to the display assembly **700**, across the inductive coupling **220, 320**. Information is advantageously transferred over this data path via the control software **1100** (FIG. **11**), described below, to the display assembly software **1200** (FIG. **12**), also described below. TABLE **1** summarizes the control input **614** for the second switch **820** on the control assembly **600** and the resulting power and data transfer to the display assembly **700**. Note that the oscillator interruptions required for sending data are short enough in duration and spaced far enough apart so as not to effect the power supply of the display circuitry.

CONTROL INPUT	POWER/DATA STATE
OPEN	DISPLAY ASSEMBLY OFF
CLOSED	DISPLAY ASSEMBLY ON
OPEN 20T	DATA "0"
OPEN 10T	DATA "1"

TABLE 1

Software Configuration

FIG. **9** illustrates a software configuration **900** for a rotating display system **100** (FIG. **1A**), including system software **1000**, control assembly software **1100** and display assembly software **1200**. The system software **1000** dictates the most abstract or high level operational aspects of the display system **100** (FIG. **1A**) via instructions **1010** communicated to the control assembly software **1100**. Advantageously, the system software **1000** incorporates a display application language rather than using a general software language. This makes it easier for individual users of the display system **100** (FIG. **1A**) or third-party suppliers to write system software programs, such as with the help of a PC-based development kit, to customize display operation. For example, the display system **100** (FIG. **1A**) may be programmed to provide custom messages for advertising, sales slogans, birthdays or anniversaries. An example of system software **1000** is described in further detail with respect to FIG. **10**, below. The display application language is described and illustrated by a simple example in the "Display Operation" section, below. The display application language set is listed and described in Appendix **A**.

As shown in FIG. **9**, an important function of the control assembly software **1100** is to interpret the system software instructions **1010** and data residing in nonvolatile memory and to carry out the operations specified. The control assembly software **1100** also transmits commands, trigger information and display data **1110** to the display assembly software **1200**. Further, the control assembly software **1110** senses motor position and provides control of the motor **160** (FIG. **1A**); sets, calculates and keeps track of time, including date and day of week; and services the push button

switch **240** (FIG. **2A**). The control assembly software **1100** is described in further detail with respect to FIG. **11**, below.

Also shown in FIG. **9**, the display assembly software **1200** receives and decodes the commands, trigger information and display data **1110** from the control assembly software **1100**. Utilizing this information, the display assembly software **1200** transmits display data to the light array **330** (FIG. **3A**). In doing so, the display assembly software **1200** translates ASCII character data to column data and controls display effects such as horizontal and vertical scrolling. The display assembly software **1200** is described in further detail with respect to FIG. **12**, below.

The system software **1000**, control assembly software **1100** and display assembly software **1200** are each resident within the display system **100** (FIG. **1A**) when the display system **100** (FIG. **1A**) is operating in a stand-alone manner. When the display system **100** (FIG. **1A**) is operating as a remote slave, such as for a stock ticker getting information from a network or computer, the system software **1000** can be accessed externally via a serial cable interface (not shown) and does not need to be resident.

System Software

FIG. **10** illustrates a particular embodiment of the system software **1000**, which comprises both instructions and data that reside in nonvolatile control assembly memory **620** (FIG. **6**), as described above. After power on initialization **1010**, all other display instruction sequences **1020-1080** are executed in a continuous loop. In a scroll greeting vertically sequence **1020**, a custom greeting (1 of 8) is loaded and scrolled vertically down into the display, held briefly and scrolled down off the display. In a similar manner, time is displayed in HH: MM AM/PM format in a scroll time vertically sequence **1030**. Next, a scroll day of week horizontally sequence **1040** is executed. In a scroll date vertically sequence **1050**, the date is then vertically scrolled into the display DD/MM/YY format. A scroll message horizontally sequence **1060** loads and scrolls a custom message (1 of 32). Finally, a revolve time sequence **1070** produces a slowly rotating 360 degree time display in HH: MM: SS format. The time rotates for approximately 2 minutes before a service selection button command **1080** is executed

and the entire process repeats. The greeting sequence **1020** cycles through a different custom greeting each time it is executed. In a similar manner, the message sequence **1060** cycles through a different custom message each time it is executed. Appendix **C** is computer program listing appendix (on CD-R) corresponding to FIG. **10**, which is written in the display application language described above.

Control Assembly Software

FIG. **11** illustrates the control assembly software **1100**, which has instructions and data that also reside in nonvolatile control assembly memory **620** (FIG. **6**). In one embodiment, the control assembly software **1100** is written in assembler, based on the particular control assembly processor **610** (FIG. **6**). Each of the instruction sequences **1110-1170** are executed in a continuous loop. In a control rotation sequence **1110**, the control assembly software **1100** polls the state of the Hall effect sensor **280** (FIG. **2B**) to determine if the magnet **554** (FIG. **5**) has been detected. The control assembly software **1100** determines the rotational speed of the motor **160** (FIG. **1A**) by measuring the time between magnet triggers. If the speed is too slow, the software **1100** increases the power to the motor **160** (FIG. **1A**). If the speed is too fast, the software **1100** decreases power to the motor **160** (FIG. **1A**). If the speed is too slow after 5 seconds of operation, the display is turned off. This is a safety feature that prevents the motor or power circuitry from damage during the event that someone or something is preventing the motor from turning. If the PWRON system software instruction (Appendix **A**) has not been encountered, the motor **160** (FIG. **1A**) remains off and control passes to the next instruction sequence **1120**. A calculate time and date sequence **1120** updates the time (hours, minutes and seconds), the date (month, day and year), and the day of the week variables residing in processor memory. These values can be modified or displayed using system software instructions.

Also shown in FIG. **11**, the service data input sequence **1130** interprets the system software **1000** (FIG. **10**). All aspects of executing the system software **1000** (FIG. **10**) are handled by this instruction sequence **1130**. These aspects include keeping track of the program counter, i.e. where the current instruction is located in system software memory, subroutine call and return addresses, and importantly, executing the

tasks specified by each system software instruction (Appendix A). The service data input sequence **1130** also services the push-button switch **240** (FIG. **2A**) and redirects program flow if the button is pressed.

Further shown in FIG. **11**, the process data input sequence **1140** provides the interpretation of data and execution of instructions retrieved from the system software **1000** (FIG. **10**). Depending on the system software display instruction, the control assembly software **1100** may take many instruction cycles to actually complete the transfer of data to the display assembly software **1200** (FIG. **12**). Many of the instructions in this sequence relate to the parsing of display information so that the display assembly software **1200** (FIG. **12**) can receive this information and act on it in an efficient manner. Besides handling "read only" or constant static display characters from the system software **1000** (FIG. **10**), the control assembly software **1100** allows the interpretation and display of "live" variables such as time and date which dynamically change. As a result, the control assembly software **1100** allows the system software **1000** (FIG. **10**) access to RAM located in control assembly processor **610** (FIG. **6**) memory. The process data input sequence **1140** provides and maintains this mechanism. Further, the process data input sequence **1140** provides the basis for horizontal and vertical scrolling effects. When a scroll mode is specified by the system software **1000** (FIG. **10**), the control assembly software **1100** is responsible for collecting the data to scroll, setting up the display assembly processor **710** (FIG. **7**) to perform the scrolling and sending the data to scroll at the correct time.

Also shown in FIG. **11**, the transmit display data sequence **1150** takes a general byte of data and transmits it over the inductive coupling **220** (FIG. **6**), **320** (FIG. **7**). The transmit display data sequence **1150** controls switch 2 **820** (FIG. **8**) in the manner described above. If switch 2 **820** (FIG. **8**) is open for a period of 20 oscillator periods, a data "0" is generated. If switch 2 **820** (FIG. **8**) is open for a period of 10 oscillator periods, a data "1" is generated. The transmit display data sequence **1150** effects the transmission of one data byte (eight bits) per sequence execution.

Further shown in FIG. **11**, the detect trigger position sequence **1160** simply waits for the Hall effect sensor **280** (FIG. **2B**) to trigger, i.e. when the magnet **554** (FIG.

5) passes under it. The magnet **554** (FIG. **5**) is placed on the motor shaft at an angle relative to the display assembly. This magnet placement along with a programmable delay in the detect trigger position sequence **1160** allows positioning of the effective display zone on the front portion of the display, as described at the end of the "Hardware Configuration - Mechanical" section, above, and further with respect to the "Display Operation" section, below. The transmit trigger data sequence **1170** transmits a trigger code over the inductive coupling **220** (FIG. **6**), **320** (FIG. **7**) in the manner of the transmit display data sequence **1150**, described above.

Display Assembly Software

FIG. **12** illustrates the display assembly software **1200**, which has instructions and data that reside in display assembly nonvolatile memory **720** (FIG. **7**). In one embodiment, the display assembly software **1200** is written in assembler, based on the particular display assembly processor **710** (FIG. **7**). The display assembly software **1200** starts executing **1201** when the control assembly software **1100** (FIG. **11**) powers-up the display assembly **700** (FIG. **7**). A retrieve input data sequence **1210** waits for commands or data from the control assembly software **1100** (FIG. **11**) coming over the inductive coupling **220** (FIG. **6**), **320** (FIG. **7**). No display function is performed until the retrieve input data sequence **1210** receives a command or data. Appendix **B** lists commands transmitted from the control assembly software **1100** (FIG. **11**) to the display assembly software **1200**.

As shown in FIG. **12**, a process input data sequence interprets commands and data from the control assembly software **1100** (FIG. **11**) and performs the appropriate function. Most of these functions simply set up data structures that are referenced when a Trigger command (Appendix **B**) is received. The Trigger command starts the modulation of the light array **330** (FIG. **1A**). If there is no Trigger command to service, a "Trigger?" decision sequence **1230** causes the display assembly software **1200** to loop through retrieving input data **1210** and processing input data **1220**. When the "Trigger?" decision sequence **1230** detects a Trigger, the display assembly software **1200** proceeds to the sequences **1240-1280** associated with the actual displaying of column information.

Also shown in FIG. **12**, a decode data sequence **1240** performs several functions depending on an operating mode. The display assembly software **1200** contains tables of all standard printable ASCII characters and the columns that make up this data. If the mode is such that character text is being displayed, the decode data sequence **1240** performs ASCII to column conversions. The decode data sequence **1240** also keeps track of the sequence of column data. Further, the decode data sequence **1240** handles other display aspects such as horizontal scrolling, vertical scrolling and bit mapped graphics.

Further, shown in FIG. **12**, once the column data has been determined, a display column datum sequence **1250** causes selected data to actually appear on the light array **330** (FIG. **1A**). A delay on time sequence **1260** keeps the light array **330** (FIG. **1A**) on for a delay period of 80 μs. Then, a column data off sequence **1270** turns-off the light array **330** (FIG. **1A**). A delay off time sequence **1280** keeps the light array **330** (FIG. **1A**) off for a period of 200 μs. Once all the columns that comprise the full viewable display have been shown in sequence, a "End?" decision sequence **1290** returns the display assembly software **1200** to normal pre-trigger data and instruction processing.

Display Operation

A detailed operational description of the rotating display system **100** (FIG. **1A**) is given here by means of the simple system software program example provided in TABLE **2**.

```
//*********************************************************
Main:
        PWRON                   // Turn motor/display on
        ImdDN "Greetings!"      // Display "Greetings!"
        DLY 100                 // Wait 100 instruction cycles
        SLEEP Main              // Turn display off for a sleep period,
                                // then repeat
//*********************************************************
```

TABLE 2

The program is written in a display application language described by example in this section and in further detail in Appendix **A** and the Display Application Language section, below. These instructions are executed sequentially. Comments are delineated by "//" and explain the operation of the program.

Power Applied

As illustrated in FIG. **11**, assume that the display system **100** (FIG. **1A**) has just been plugged in, i.e. power has been applied. The control assembly software **1100** will start up and begin executing the loop of instruction sequences **1110-1170** described with respect to FIG. **11**, above. Processing begins with the control rotation instruction sequence **1110**. Because no instructions from the system software Table **2** have been executed yet, the control rotation sequence **1110** is exited without action. The calculate time and date sequence **1120** is executed although, because the display system **100** (FIG. **1A**) has just been powered on, the correct time and date have yet to be entered. For simplicity, the ability to set or display time, date or day of week information are not included in this example. Thus, no further mention is made of the calculate time and date sequence **1120** below. Time has some relevance to the SLEEP instruction (Appendix **A**) in that the correct elapsed time must be measured, but it is assumed throughout this example that the calculate time and date sequence **1120** is continually keeping track of time.

PWRON

Also illustrated in FIG. **11**, the next instruction sequence to be processed is service data input **1130**. At this time the control assembly software **1100** fetches the first system software instruction, which, as shown in Table **2**, is PWRON. The PWRON instruction is stored for use by the process data input sequence **1140**, which executes the instruction, i.e. performs the functions associated with the PWRON instruction. These functions include enabling the motor **160** (FIG. **1A**), enabling the control rotation sequence **1110**, applying power to the display assembly **300** (FIG. **1A**) and determining whether the motor **160** (FIG. **1A**) is spinning correctly. If the motor **160** (FIG. **1A**) is not spinning correctly, the control assembly software **1100** shuts off power to both the motor **160** (FIG. **1A**) and the display assembly **300** (FIG. **1A**) and

suspends program execution. If the motor **160** (FIG. **1A**) is spinning correctly, the traverse through the control assembly software loop **1110-1170** continues.

The transmit display data sequence **1150** does not send display data at this time because the PWRON instruction does not require it. The detect trigger position sequence **1150** detects a trigger point as the magnet **554** (FIG. **5**) passes under the Hall-effect sensor **280** (FIG. **2B**), but no trigger command is sent to the display assembly software **1200** (FIG. **12**), again because the PWRON instruction does not require it. This completes one system software instruction cycle, and another cycle begins at the beginning of the control assembly software loop **1110-1170**.

On this next pass of the control assembly software loop **1110-1170**, because the motor **160** (FIG. **1A**) has been enabled, the control rotation instruction sequence **1110** operates to ensure the speed of the motor is within tolerance. In one embodiment, the motor **160** (FIG. **1A**) speed is about 900 rpm +/- 100 rpm. In subsequent passes, the control rotation sequence **1110** continues the same function of controlling the motor motor **160** (FIG. **1A**). Thus, no further mention is made of the control rotation sequence **1110** below.

ImdDN "Greetings"

Further illustrated in FIG. **11**, another system software instruction is fetched during the service data input sequence **1130**. On this pass, the instruction is ImdDN with the parameter "Greetings!" ImdDN stands for "Immediate addressing, Display Normal mode." All of the Imd class system software instructions use immediate addressing, which means that the character data associated with the instructions are located in memory immediately following the instruction itself. All of the DN type system software instructions are "normal display" functions, meaning there are no special scrolling effects associated with the instruction's execution.

ImdDN causes several things to happen. First of all, the process data input block saves the instruction so that subsequent system software memory accesses are interpreted as character data. Thus, no more instructions will be interpreted until the character string parameter of the ImdDN instruction has been read and processed. Until all of the data, in this case the characters 'G', 'r', 'e', 'e', 't', 'i', 'n', 'g', 's', '!,' have

been read, the control assembly software **1100** will execute its loop of instruction sequences **1110-1170** only gathering data and processing it. Before the first data byte is processed, the control assembly software **1100** sends a mode byte to the display assembly software **1200** (FIG. **12**) via the inductive coupling **220** (FIG. **6**), **320** (FIG. **7**) between the control assembly **200** (FIG. **2A**) and the display assembly **300** (FIG. **3A**).

The transmission of the mode byte to the display assembly software **1200** (FIG. **12**) allows it to handle subsequent data in an appropriate manner. In this case, the mode is normal with no scroll effects. Each byte of data, such as the first 'G' in "Greeting," is sent in sequence via the inductive coupling **220** (FIG. **6**), **320** (FIG. **7**) to the display assembly software **1200** (FIG. **12**), as described above. This occurs at a rate of one character per control assembly software cycle, i.e. one pass through the loop **1110-1170**. When all the data has been processed, the control assembly software **1100** completes the processing of the ImdDN command by enabling trigger transmissions. From this point, a trigger command is sent to the display assembly software **1200** (FIG. **12**) on each pass through the transmit trigger data sequence **1170**. In this example, once the ImdDN instruction and associated parameter data have been processed, when the next trigger position is sensed, the control assembly software **1100** sends a trigger command byte to the display assembly software **1200** (FIG. **12**).

As illustrated in FIG. **12**, a retrieve input data sequence **1210** receives data from the control assembly software **1100** (FIG. **11**), such as the 'G' in "Greeting." The process input data sequence **1220** places the data in a display buffer, such as a data RAM portion of the display assembly processor **710** (FIG. **7**), as the data is received. Once a trigger command has been received from the control assembly software **1100** (FIG. **11**), the process input data sequence **1220** passes the trigger command to the "Trigger?" decision sequence **1230**. Then, control passes to the decode data sequence **1240**, which checks the mode of the display (in this case normal, no scrolling effects), retrieves the ASCII 'G' character (the first character of Greeting!") from the data buffer, and performs a table lookup to fetch the first column data associated with the 'G' character. A display column datum sequence **1250** writes the column data to the light array **330** (FIG. **1A**). A delay on time sequence **1260** allows the column data to remain

displayed for 80 μs. A column data off sequence **1270** turns off the light array **330** (FIG. **1A**). Because this is only the first column, the "End?" condition of a decision sequence **1290** is not satisfied. A delay off time sequence **1280** keeps the light array **330** (FIG. **1A**) off for 200 μs. Next, the decode data sequence **1240** fetches the second column of the ASCII 'G' and the process repeats. Once all columns of all characters in the data buffer have been sequentially displayed, control returns to the retrieve data input sequence **1210**. Each time the display assembly software **1200** receives a trigger command from the control assembly software **1100** (FIG. **11**), this entire display process repeats.

DLY 100

Meanwhile, in the control assembly software **1100** (FIG. **11**), the next system software instruction is ready for execution. This instruction is the DLY instruction with an accompanying parameter of "100." This instruction does nothing for 100 cycles of the control assembly software loop **1110-1170** (FIG. **11**) while still allowing trigger instructions to be passed to the display assembly software 1200. The net effect is that the display will be showing the characters "Greetings!" for 7.5 seconds. That is, at 800 rpm the motor **160** (FIG. **1A**) rotates once every 75 ms, and 75ms times 100 delay cycles is 7.5 seconds.

SLEEP Main

After the DLY instruction has completed, the next system software instruction, SLEEP, is queued. The SLEEP instruction turns off the motor **160** (FIG. **1A**), turns off display system power and suspends program execution a pre-defined amount of time, such as 5 minutes. Once the sleep time has elapsed, program execution resumes at the address specified in the sleep parameter, "Main." Summarizing the example, the system software (Table **2**) causes the display system **100** (FIG. **1A**) to operate indefinitely, displaying the message "Greetings!" for about 8 seconds, then shutting off for 5 minutes then repeating the process. One of ordinary skill in the art can extrapolate the operation of this example, although a simple one, to the operation of more complex system software implementations, such as disclosed in FIG. **10** and a corresponding computer program listing Appendix **C**.

Display Application Language

The system software display application language utilizes an instruction set that performs the specific tasks that a display would normally perform. Tasks such as displaying a set of characters ("Hello!") and scrolling these characters vertically or horizontally are all incorporated in this instruction set. The display application language instruction set is listed and described in Appendix **A** and, for some instructions, additionally below.

SETT allows the system software to set the correct day of the week, time and date by accessing a data RAM portion of the control assembly processor **610** (FIG. **6**). Through the use of other instructions, variables may be written to data RAM to provide the current calendar and time information. When SETT is executed, these variables are loaded into a real time clock **630** (FIG. **6**) that is then automatically serviced as long as power is applied to the rotating display system.

FLOAT is used to alter the timing of the display trigger point, as described above, such that the viewable display area can rotate 360 degrees around the cylindrical circumference of the display.

SYNC is used to transition from the FLOAT mode. It restores the trigger point to its normal center position at the "front" of the display, as described above.

NEXT is an important instruction used in conjunction with the push button switch **240** (FIG. **2A**). The parameter to NEXT is a system software address. If the switch **240** (FIG. **2A**) is pushed at any time during the execution of the system software, program execution will continue at the address specified by the NEXT parameter. This allows the rotating display system to provide a user-friendly interface for the prompting of user input.

The rotating display system has been disclosed in detail in connection with various embodiments of the present invention. These embodiments are disclosed by way of examples only and are not to limit the scope of the present invention, which is defined by the claims that follow. One of ordinary skill in the art will appreciate many variations and modifications within the scope of this invention.

APPENDIX A: SYSTEM SOFTWARE INSTRUCTIONS

Display related instructions:

ImdDN: (Immediate addressing, Display Normal), Display the set of characters immediately following this instruction, no scrolling.

ImdDV: (Immediate addressing, Display Vertical scroll), Display the set of characters immediately following this instruction, vertical scroll.

ImdDH: (Immediate addressing, Display Horizontal scroll), Display the set of characters immediately following this instruction, horizontal scroll.

DirDN: (Direct addressing, Display Normal), Display a set of characters located at the address following the instruction, no scrolling.

DirDV: (Direct addressing, Display Vertical scroll), Display a set of characters located at the address following the instruction, vertical scroll.

DirDH: (Direct addressing, Display Horizontal scroll), Display a set of characters located at the address following the instruction, horizontal scroll.

StblDN: (Short Table, Display Normal), Display a set of characters in a short table by address and index, no scrolling.

StblDV: (Short Table, Display Vertical scroll), Display a set of characters in a short table by address and index, vertical scroll.

StblDH: (Short Table, Display Horizontal scroll), Display a set of characters in a short table by address and index, horizontal scroll.

LtblDN: (Long Table, Display Normal), Display a set of characters in a long table by address and index, no scrolling.

LtblDV: (Long Table, Display Vertical scroll), Display a set of characters in a long table by address and index, vertical scroll.

LtblDH: (Long Table, Display Horizontal scroll), Display a set of characters in a long table by address and index, horizontal scroll.

General instructions:

SETT: (Set Time), Set time/date/day of week.

RTN: (Return), Return from subroutine.

PWRON: (Power On), Turn motor and power to display on.

PWROFF: (Power Off), Turn motor and power to display off.

SYNC: (Synchronize), Use absolute position for display trigger.

DLY: (Delay), Delay a number of instruction cycles.

FLOAT: (Float), Use relative position for display trigger.

JUMP: Jump to another program instruction.

CALL: Call a subroutine.

ADD: Add two data bytes.

AND: Logical And of two data bytes.

OR: Logical Or of two data bytes.

COPY: Copy a data byte from one address to another.

WRITE: Write constant data to address in controller memory.

IFZ: (If Zero), If a data byte is zero, skip next instruction.

NEXT: Store a jump address for the next button press.

SLEEP: Disable display/motor and stop executing instructions for a specified time.

POKED: (Poke Display), Poke a value at a data address in the display processor.

APPENDIX B: CONTROL ASSEMBLY TO DISPLAY ASSEMBLY COMMANDS

Trigger: Causes the Display software to process and display column data.

SysReset: (System Reset), Re-initializes all the Display software variables.

PokeVar: (Poke Variable), Stores data byte at address.

TestMsg: (Test Message), Test message displayed on Trigger command.

TestLEDs: Causes a specified LED to momentarily flash.

FillBtMp: (Fill Bit Map), Fills a bit map data area in memory.

PutBtMp: (Put Bit Map), Places a stream of data in bit map memory.

InvBitMap: (Invert Bit Map), Changes all bit map data "1"s to "0"s and "0"s to "1"s.

PutChar: (Put Character), Places data in memory and/or sets the buffer pointer.